

Universal Transmitter

The Universal Transmitter has been specifically designed to enable hardwired inputs to be relayed out to the PAG8 paging system using radio technology. This allows property managers to have fully integrated fire and alarm systems situated away from the main house (for example barns, outhouses) to be linked to their main PAG8 system.

Triggers

1. Volt free contact that may be set to normally open or normally closed using an onboard link setting
2. Opto isolated input will accept 6, 12, or 24v AC or DC
3. A test button placed on the front is provided for convenience

LED indicator

A blue LED light flashes when a trigger event occurs.

RF Output

A B.N.C connection is provided to take a short Helical (rubber duck) or larger dipole aerial. The larger dipole aerial may be used if extended range is required.

Legacy
Universal Transmitter

Property, People Protection



Universal Transmitter

Sentinor Legacy 407-S Pendant		
Power Source	4x AA Batteries	
External Power Source	7-15v AC or 7-21v DC External Power Source	
Functionality	1x Alarm signal	
RF Frequency	173.225MHz	
Range	1km over flat, open ground. Multipliers should be applied to assist range est..	
	Path	Multiplier
	Open, Line of sight	1
	Open, Obscured Path (trees etc)	0.3-0.9
	Built up area	0.2-0.5
	In building (brick)	0.3-0.8
	In building (Reinforced concrete)	0.05-0.3
	In tunnels	0.05-0.9
Antenna Type	Helical (rubber duck)	