

LEGACY 407-S PENDANT

Sentinor's Legacy 407-S Pendant transmitter has been designed and engineered to be a direct replacement for the 4601-50 style pendant transmitter. It works harmoniously with any 4600 series radio systems.

Direct Replacement:

- Using our vast knowledge of Military graded radio technology; we have engineered the pendant to allow configuration to any Scantronic 173.225MHz system.
- This allows the Sentinor Legacy Pendant to be integrated in to Fire, Security or Nurse calling alarm system using 173.225MHz receivers.

Functionality:

- The Sentinor Legacy Pendant is triggered by a single button on the front of the pendant. Transmission is confirmed by a light-blue LED which will stay lit for approx. 1-2 seconds.

HARDWARE

- Casing made of a reinforced ABS, flame-retardant, plastic enclosure.
- Trigger button composed of a moulded silicone rubber material.
- Aerial cord is made of a special, non-allergenic material, allowing for the pendant to be worn around the neck of the individual. A special push/pull connection has been designed so the aerial will not break.
- Unit is splash resistant (ie not designed to be fully submerged).

**Legacy
407-S Pendant**

**DESIGNED TO BE AN IMPROVED
REPLACEMENT FOR THE SCANTRONIC
4601-50 PENDANT**



SPECIFICATIONS:

Sentinor
Legacy
407-S
Pendant



Sentinor Legacy 407-S Pendant		
Power Source	3v lithium-manganese dioxide CR2032 battery	
Battery Life	Sentinor recommends the user replace the battery annually	
Functionality	1x button, 1x Alarm signal	
RF Frequency	173.225MHz	
Range	1km over flat, open ground. Multipliers should be applied to assist range est..	
	Path	Multiplier
	Open, Line of sight	1
	Open, Obscured Path (trees etc)	0.3-0.9
	Built up area	0.2-0.5
	In building (brick)	0.3-0.8
	In building (Reinforced concrete)	0.05-0.3
	In tunnels	0.05-0.9
Antenna Type	1/2 wave flexible whip (necklace)	
Dimensions	35mm x 70mm x 18mm	